



PARTS	RATIO	SPEED (RPM)	LOAD (Nm In-lbs)	PARTS	RATIO	SPEED (RPM)	LOAD (Nm In-lbs)
MPG60-03	3:1	500	0.07 0.620	MPG60-36	36:1	41	0.67 4.16
MPG60-05	5:1	300	0.10 0.885	MPG60-40	40:1	37.5	0.74 6.55
MPG60-06	6:1	250	0.12 1.062	MPG60-50	50:1	30	0.93 8.23
MPG60-7.5	7.5:1	200	0.16 1.42	MPG60-60	60:1	25	1.01 8.94
MPG60-10	10:1	150	0.21 1.86	MPG60-75	75:1	20	1.26 11.15
MPG60-12.5	12.5:1	120	0.26 2.30	MPG60-90	90:1	16	1.51 13.36
MPG60-15	15:1	100	0.31 2.74	MPG60-100	100:1	15	1.68 14.87
MPG60-18	18:1	83	0.37 3.27	MPG60-120	120:1	12.5	2.52 22.30
MPG60-20	20:1	75	0.37 3.27	MPG60-150	150:1	10	2.52 22.30
MPG60-25	25:1	60	0.47 4.16	MPG60-180	180:1	8	3.00 26.55
MPG60-30	30:1	50	0.56 5.96				

Power (W)	Voltage (VAC)	Rated Current (A)	Starting Torque (mNm)	Rated Speed (RPM)	Rated Torque (mNm)	Capacitor (μF)
4	115/ph	0.21	40	1450	30	3

Unit: mm	Technical reference	Created by	Approved by
		Document type	Document status
		Title	
		AC60 4W Series	AC GEAR MOTOR
Rev.	Date of issue	Sheet	