



320 ± 20mm

PARTS	RATIO	SPEED (RPM)	LOAD (Nm In-lbs)	PARTS	RATIO	SPEED (RPM)	LOAD (Nm In-lbs)
MPG60-03	3:1	500	0.1 0.89	MPG60-36	36:1	41	1.0 8.85
MPG60-05	5:1	300	0.16 1.42	MPG60-40	40:1	37.5	1.12 9.91
MPG60-06	6:1	250	0.19 1.68	MPG60-50	50:1	30	1.4 12.39
MPG60-7.5	7.5:1	200	0.23 2.04	MPG60-60	60:1	25	1.51 13.36
MPG60-10	10:1	150	0.31 2.74	MPG60-75	75:1	20	1.89 16.73
MPG60-12.5	12.5:1	120	0.39 3.45	MPG60-90	90:1	16	2.27 20.09
MPG60-15	15:1	100	0.46 4.07	MPG60-100	100:1	15	2.52 22.3
MPG60-18	18:1	83	0.56 4.96	MPG60-120	120:1	12.5	3.0 26.55
MPG60-20	20:1	75	0.56 4.96	MPG60-150	150:1	10	3.0 26.55
MPG60-25	25:1	60	0.7 6.20	MPG60-180	180:1	8	3.0 26.55
MPG60-30	30:1	50	0.84 7.43				

AC60-115-6 MOTOR SPECIFICATIONS						
Power (W)	Voltage (VAC)	Rated Current (A)	Starting Torque (mNm)	Rated Speed (RPM)	Rated Torque (mNm)	Capacitor (µF)
6	115/ph	0.23	70	1550	40	0.8

Unit: mm	Technical reference	Created by	Approved by
		Document type	Document status
		Title AC60 6W Series	
Rev.	Date of issue	Sheet	

AC GEAR MOTOR

AC60 6W Series