



PARTS	RATIO	SPEED (RPM)	LOAD (Nm In-lbs)	PARTS	RATIO	SPEED (RPM)	LOAD (Nm In-lbs)
MPG80-03	3:1	500	0.67 5.93	MPG80-36	36:1	41	6.48 57.35
MPG80-05	5:1	300	1.00 8.85	MPG80-40	40:1	37.5	6.51 57.62
MPG80-06	6:1	250	1.20 10.62	MPG80-50	50:1	30	8.13 71.96
MPG80-7.5	7.5:1	200	1.5 13.28	MPG80-60	60:1	25	9.8 86.74
MPG80-10	10:1	150	2.0 17.70	MPG80-75	75:1	20	10.0 88.51
MPG80-12.5	12.5:1	120	2.5 22.13	MPG80-90	90:1	16	10.0 88.51
MPG80-15	15:1	100	3.0 26.55	MPG80-100	100:1	15	10.0 88.51
MPG80-18	18:1	83	3.24 28.68	MPG80-120	120:1	12.5	10.0 88.51
MPG80-20	20:1	75	3.6 31.86	MPG80-150	150:1	10	10.0 88.51
MPG80-25	25:1	60	4.5 39.83	MPG80-180	180:1	8	10.0 88.51
MPG80-30	30:1	50	5.4 47.79				

AC90-115-40 MOTOR SPECIFICATIONS						
Power (W)	Voltage (VAC)	Rated Current (A)	Starting Torque (mNm)	Rated Speed (RPM)	Rated Torque (mNm)	Capacitor (µF)
40	115/ph	0.63	250	1650	220	10

Unit: mm	Technical reference	Created by	Approved by
		Document type	Document status
		Title AC90 40W Series	
		Rev.	Date of issue
		Sheet	